

DM-B4310-A1

Digital Module




- Can–bus interface
- Applied for static weighing
- A/d convertor
- Digital filtering, programmable
- Selectable measuring speed
- Nonvolatile storage
- Anti–reverse, anti–overvoltage, tvs protection.

Frequency-temp. chart (20) ℃



Temp.-non-linearity chart (10Hz)




Specifications

Items	Unit	Specification
Accuracy	%	0.002
Measuring frequency	Hz	Rated：10 Max：80
A/D conversion bit	Bit	20
Measuring signal range	mV/V	±3.0
Communication interface	—	CAN
Baud rate	bits/s	10K/20K/50K/125K/250K/500K/800K/1000K
Digital filtering	—	Moving average filtering/ recursive filtering
Bridge input resistance	Ω	>100
Excitation voltage	V	5
Drift on zero	ppm/℃	75
Drift on span	ppm/℃	75
Working voltage/accuracy	V/%	8 ~ 26/0.1
Working current	mA	16
Nominal temperature	℃	−10 ~ 40
Operation temperature	℃	−20 ~ 85
Support sensors qty	pcs	1
Installation	—	Built−in
Size	mm	Φ32

Note：1）Accuracy is based on rated frequency and nominal temperature。
2）The measuring frequency can be set in range smaller than Max value.
3）The signal sensitivity for test is 2.0mV/V.

Frequency	10Hz	20Hz	40Hz	80Hz	Temp.	−20℃	−10℃	20℃	40℃	85℃
Accuracy	0.002%	0.008%	0.01%	0.014%	Non-linearity	0.0017%	0.002%	0.0007%	0.0003%	0.0007%

Wiring



AVIC ZHONGHANG ELECTRONIC MEASURING INSTRUMENTS CO.,LTD.

Add: No. 166, West Avenue, Hi−Tech District, Xi'an, Shaanxi, China.
Tel: +86−29−61807888
Fax: +86−29−61807898
Email: admin@zemic.com.cn

There is no special declaration if any change in the specification.
ZEMIC reserves the rights in the final interpretation and modification.